RO6350

Incremental encoder with hollow shaft


RO-5000-I24/N1U




Article to be discontinued

Alternative articles: ROP521 + E12402

When selecting an alternative article and accessories please note that technical data may differ!





Product characteristics		
Resolution		5000 resolution
Shaft design		hollow shaft open to one side
Shaft diameter	[mm]	12
Application		
Function principle		incremental
Electrical data		
Operating voltage	[V]	1030 DC
Current consumption	[mA]	< 150
Outputs		
Electrical design		HTL
Max. current load per output	[mA]	50
Switching frequency	[kHz]	300
Type of short-circuit protection		< 60 s
Phase difference A und B	[°]	90
Measuring/setting range		
Resolution		5000 resolution
Operating conditions		
Ambient temperature	[°C]	-40100
Max. relative air humidity	[%]	98
Protection		IP 64; (on the housing: IP 67; on the shaft: IP 64)

ifm efector, inc. • 1100 Atwater Drive • Malvern • PA 19355 — We reserve the right to make technical alterations without prior notice. — EN-US — RO6350-02 — 01.09.2010 — 🚊

RO6350

Incremental encoder with hollow shaft



RO-5000-I24/N1U

Tests / approvals			
Shock resistance		200 g	
Vibration resistance		30 g	
MTTF	[years]	190	
Mechanical data			
Weight	[g]	444.4	
Dimensions	[mm]	Ø 58 / L = 35.5	
Material		aluminum	
Max. revolution, mechanical [U/min]		12000	
Max. starting torque	[Nm]	1	
Reference temperature torque	[°C]	20	
Shaft design		hollow shaft open to one side	
Shaft diameter	[mm]	12	
Shaft fit		H7	
Shaft material		stainless steel	
Installation depth/shaft	[mm]	10	
Max. axial shaft misalignme	nt [mm]	1; (max. radial shaft alignment: ± 0,05 mm)	
Electrical connection			
Cable: 1 m, PUR; Maximum cable length: 300 m; radial, can also be used axially			
brown A green A inverted grey B pink B inverted red 0 index black 0 index inverted blue L+ sensor white 0V sensor brown/green L+ (Up) white/green 0V (Un) screen housing lilac error inverted Diagrams and graphs Pulse diagram			
		Direction of rotation clockwise (looking at the shaft)	