RO6348

Incremental encoder with hollow shaft


RO-3600-I24/N1U




Article no longer available - archive entry

Alternative articles: ROP521 + E12402

When selecting an alternative article and accessories please note that technical data may differ!





Product characteristics		
Resolution		3600 resolution
Shaft design		hollow shaft open to one side
Shaft diameter	[mm]	12
Application		
Function principle		incremental
Electrical data		
Operating voltage	[V]	1030 DC
Current consumption	[mA]	< 150
Outputs		
Electrical design		HTL
Max. current load per output	[mA]	50
Switching frequency	[kHz]	300
Type of short-circuit protection		< 60 s
Phase difference A and B	[°]	90
Measuring/setting range		
Resolution		3600 resolution
Operating conditions		
Ambient temperature	[°C]	-40100
Max. relative air humidity	[%]	98
Protection		IP 64; (on the housing: IP 67; on the shaft: IP 64)

ifm electronic gmbh • Friedrichstraße 1 • 45128 Essen — We reserve the right to make technical alterations without prior notice. — EN-GB — RO6348-02 — 01.09.2010 — 🚊

RO6348

Incremental encoder with hollow shaft



RO-3600-I24/N1U

Tests / approvals	5			
Shock resistance		200 g		
Vibration resistant	ce	30 g		
Mechanical data				
Weight	[g]	436.2		
Dimensions	[mm]	Ø 58 / L = 35.5		
Materials		aluminium		
Max. revolution, mechanical [U/min]		12000		
Max. starting torq	ue [Nm]	1		
Reference temper torque	ature [°C]	20		
Shaft design		hollow shaft open to one side		
Shaft diameter	[mm]	12		
Shaft fit		H7		
Shaft material		stainless steel		
Installation depth of shaft [mm]		10		
Max. axial shaft misalignment [mm]		1; (max. radial shaft alignment: ± 0,05 mm)		
Electrical connection				
Cable: 1 m, PUR; Maximum cable length: 300 m; radial, can also be used axially				
brown green grey pink red black blue white brown/green white/green screen lilac	A A inverted B B inverted 0 index 0 index inverted L+ sensor 0V sensor L+ (Up) 0V (Un) housing failure inverted			
Diagrams and graphs				
Pulse diagram				

direction of rotation clockwise (looking at the shaft)