



Through-beam sensor receiver

OAE-FPKG/T/US

Article no longer available - archive entry



- 1 selection switch and potentiometer under cover
receiver in upper lens

Product characteristics

| | |
|---------|-------------|
| Housing | rectangular |
|---------|-------------|

Application

| | |
|--------------------|-----------------------|
| Special feature | Function check output |
| Function principle | Through-beam sensor |

Electrical data

| | |
|-----------------------------|------------|
| Operating voltage [V] | 10...36 DC |
| Current consumption [mA] | < 50 |
| Protection class | II |
| Reverse polarity protection | yes |

Outputs

| | |
|--|--|
| Electrical design | PNP |
| Output function | light-on/dark-on mode; (parameterisable) |
| Function check output | yes |
| Max. current load for function check output [mA] | 10 |
| Permanent current rating of switching output DC [mA] | 250 |

OA5115



Through-beam sensor receiver

OAE-FPKG/T/US


| | | |
|---------------------------------------|------------------|---|
| Max. current load in dual output mode | [mA] | 100 |
| Switching frequency DC | [Hz] | 300 |
| Short-circuit protection | | yes |
| Type of short-circuit protection | | pulsed |
| Overload protection | | yes |
| Time function | [s] | 0.5...10 |
| Detection zone | | |
| Transmitter / receiver | | receiver |
| Range | [m] | < 50 |
| Range adjustable | | yes |
| Operating conditions | | |
| Ambient temperature | [°C] | -25...60 |
| Protection | | IP 65 |
| Tests / approvals | | |
| EMC | EN 60947-5-2 | |
| | EN 55011 | class B |
| Mechanical data | | |
| Housing | | rectangular |
| Dimensions | [mm] | 90 x 30 x 70 |
| Materials | | PPO modified |
| Lens material | | PMMA |
| Displays / operating elements | | |
| Display | switching status | 1 x LED, yellow |
| | operation | 1 x LED, green |
| | function | 1 x LED, red |
| Operating elements | | on-delay or off-delay selectable via slide switch |
| Accessories | | |
| Items supplied | | Angle bracket screwdrivers |
| Remarks | | |
| Pack quantity | | 1 pcs. |
| Electrical connection | | |
| Connector: 1 x M12; coding: A | | |
| | | |



Through-beam sensor receiver

OAE-FPKG/T/US

Connection



2

Function check output