## RB6002

## Incremental encoder with solid shaft

RB-0020-124/L2



phase-out article Alternative articles: RB3500 When selecting an alternative article and accessories please note that technical data may differ! 1 37,5 25 (O  $\mathcal{O}$ 1 2 reference mark M3 Depth 5 mm CE 👜 **Product characteristics** Resolution 20 resolution Shaft design solid shaft Shaft diameter [mm] 6 Application Function principle incremental Electrical data Operating voltage [V] 10...30 DC Current consumption [mA] 150 Outputs Electrical design HTL Max. current load per output [mA] 50 Switching frequency [kHz] 160 Type of short-circuit < 60 s protection Phase difference A and B [°] 90 Measuring/setting range Resolution 20 resolution **Operating conditions** Ambient temperature [°C] -40...70 Note on ambient temperature for firmly laid cable Max. relative air humidity [%] 75; (briefly: 95 %) Protection IP 64

## **RB6002**

## Incremental encoder with solid shaft



RB-0020-I24/L2

<b>T</b>		
Tests / approvals		
Shock resistance		100 g (6 ms)
Vibration resistance		10 g (552000 Hz)
MTTF	[years]	190
Mechanical data		
Weight	[g]	258.6
Dimensions	[mm]	Ø 35 / L = 52.5
Materials		aluminium
Max. revolution, mechanical [U/min]		10000
Max. starting torque	[Nm]	1
Reference temperature torque	[°C]	20
Shaft design		solid shaft
Shaft diameter	[mm]	6
Shaft material		steel (1.4104)
Max. shaft load axial (at the shaft end)	[N]	5
Max. shaft load radial (at the shaft end)	e [N]	10
Electrical connection		
Cable: 2 m, PUR; radial, can also be used axially		
brown A		
green 0 V A		
grey B pink 0 V B		
red 0 index		
black 0 V 0 ind	ex	
brown/green L+ (Up)		
white/green L- 0 V (U		
lilac failure inv screen housing	verted	
Diagrams and graphs		
Pulse diagram		
		direction of rotation clockwise (looking at the shaft)