
IE5054

Inductive sensor

IE-3001-BNOG/10m



Article no longer available - archive entry



| Product characteristics | | |
|---|------|-----------------|
| Electrical design | | NPN |
| Output function | | normally closed |
| Sensing range | [mm] | 1 |
| Housing | | Threaded type |
| Dimensions | [mm] | M8 x 1 |
| Electrical data | | |
| Operating voltage | [V] | 1036 DC |
| Current consumption | [mA] | < 7 |
| Protection class | | II |
| Reverse polarity protection | | no |
| Outputs | | |
| Electrical design | | NPN |
| Output function | | normally closed |
| Max. voltage drop switching output DC | [V] | 1.5 |
| Permanent current rating of switching output DC | [mA] | 100 |
| Switching frequency DC | [Hz] | 1000 |
| Short-circuit protection | | no |
| Overload protection | | no |
| Monitoring range | | |
| Sensing range | [mm] | 1 |
| Real sensing range Sr | [mm] | 1 ± 10 % |
| Operating distance | [mm] | 00.8 |
| | | |


IE5054

Inductive sensor

IE-3001-BNOG/10m



| Accuracy / deviations | | | | | |
|--|-----------|------------------|---|--|--|
| Correction factor | | steel: 1 / stair | lless steel: 0.7 / brass: 0.4 / aluminum: 0.3 / copper: 0.2 | | |
| Hysteresis | [% of Sr] | 115 | | | |
| Switch-point drift | [% of Sr] | -1010 | | | |
| Operating conditions | | | | | |
| Ambient temperature | [°C] | | -2580 | | |
| Protection | | IP 67 | | | |
| Mechanical data | | | | | |
| Housing | | | Threaded type | | |
| Mounting | | | flush mountable | | |
| Dimensions | [mm] | M8 x 1 | | | |
| Thread designation | | M8 x 1 | | | |
| Displays / operating elements | | | | | |
| Display | | Switching status | 1 x LED, yellow | | |
| Accessories | | | | | |
| Items supplied | | | lock nuts: 2 | | |
| Remarks | | | | | |
| Pack quantity | | | 1 pcs. | | |
| Electrical connection | | | | | |
| Cable: 10 m, PVC; 3 x 0.14 mm ² | | | | | |
| Connection | | | | | |



Core colors :

BN = brown
BU = blue
BK = black