## IF0030

### Inductive sensor

IFA2004-BBOW/6M



# 

( (

Product characteristics		
Output function		normally closed
Sensing range	[mm]	4
Housing		Threaded type
Dimensions	[mm]	M12 x 1 / L = 71
Electrical data		
Frequency AC	[Hz]	4763
Operating voltage	[V]	20250 AC
Protection class		II
Reverse polarity protection	1	no
Outputs		
Output function		normally closed
Max. voltage drop switchin output AC	g [V]	8.5
Minimum load current	[mA]	8
Max. leakage current	[mA]	2
Permanent current rating of switching output AC	of [mA]	200; (250 (50 °C))
Short-time current rating of switching output	f [mA]	900; (20 ms / 0,5 Hz)
Switching frequency AC	[Hz]	25
Short-circuit proof		no
Overload protection		no
Monitoring range		
Sensing range	[mm]	4
Real sensing range Sr	[mm]	4 ± 10 %
Operating distance	[mm]	03.25
Accuracy / deviations		
Correction factor		steel: 1 / stainless steel: 0.7 / brass: 0.4 / aluminum: 0.3 / copper: 0.2
Hysteresis	[% of Sr]	115
Switch-point drift	[% of Sr]	-1010


## IF0030

### **Inductive sensor**





Operating conditions					
Ambient temperature	[°C]	-2580			
Protection		IP 67			
Tests / approvals					
EMC		EN 60947-5-2			
		EN 55011	class B		
MTTF	[years]	932			
Mechanical data					
Housing		Threaded type			
Mounting		non-flush mountable			
Dimensions	[mm]	M12 x 1 / L = 71			
Thread designation			M12 x 1		
Material		housing	g: brass white bronze coated; sensing face: PBT		
Displays / operating elements					
Display		Switching status	1 x LED, yellow		
Electrical connection					
Required protection		miniature fuse to IEC60127-2 sheet 1; $\leq$ 2 A; fast acting			
Accessories					
Items supplied		lock nuts: 2			
Remarks					
Remarks		Recommendation: check the unit for reliable function after a short circuit.			
Pack quantity		1 pcs.			
Electrical connection					
Cable: 6 m, PVC; 2 x 0.5 mm <sup>2</sup>					
Connection					



Note miniature fuse to IEC60127-2 sheet  $1 \le 2$  A fast acting

Core colors :

BN = brown BU = blue