IF0186

Inductive sensor


IFA2004-BBOW/V4A



Article no longer available - archive entry

Alternative articles: IF0261

When selecting an alternative article and accessories please note that technical data may differ!



| Product characteristics | | |
|--|-----------|--|
| Output function | | normally closed |
| Sensing range | [mm] | 4 |
| Housing | | Threaded type |
| Dimensions | [mm] | M12 x 1 / L = 71 |
| Electrical data | | |
| Frequency AC | [Hz] | 4763 |
| Operating voltage | [V] | 90250 AC |
| Protection class | | Π |
| Reverse polarity protection | | no |
| Outputs | | |
| Output function | | normally closed |
| Max. voltage drop switching output AC |) [V] | 8.5 |
| Minimum load current | [mA] | 8 |
| Max. leakage current | [mA] | 3 (250 V AC) / 1.5 (120 V AC) |
| Permanent current rating of switching output AC | [mA] | 200; (250 (50 °C)) |
| Short-time current rating of switching output | [mA] | 900; (20 ms / 0,5 Hz) |
| Switching frequency AC | [Hz] | 25 |
| Short-circuit protection | | no |
| Overload protection | | no |
| Monitoring range | | |
| Sensing range | [mm] | 4 |
| Real sensing range Sr | [mm] | 4 ± 10 % |
| Operating distance | [mm] | 03.25 |
| Accuracy / deviations | | |
| Correction factor | | steel: 1 / stainless steel: 0.7 / brass: 0.4 / aluminum: 0.3 / copper: 0.2 |
| Hysteresis | [% of Sr] | 115 |

IF0186

Inductive sensor

IFA2004-BBOW/V4A



| [% of Sr] | -1010 |
|-----------|--------------------------------------|
| | |
| [°C] | -2580 |
| | IP 67 |
| | |
| | Threaded type |
| | non-flush mountable |
| [mm] | M12 x 1 / L = 71 |
| | M12 x 1 |
| | stainless steel (1.4571/316Ti); PBT |
| nents | |
| | Switching status 1 x LED, yellow |
| | |
| | lock nuts: 2 |
| | |
| | 1 pcs. |
| | |
| 1m² | |
| | |
| | |
| | |
| | |
| | BNL1 |
| | |
| | |
| | |
| | |
| | |
| | [°C] |

| | Core colors : |
|------|---------------|
| BN = | brown |
| BU = | blue |