Pressure sensor with LED bar display





Article no longer available - archive entry 2 48 22 23 48 48 61/4 LED display Programming button

ϵ

Product characteristics			
Number of inputs and outputs		Number of digital outputs: 1	
Measuring range	[kPa]	0100	
Process connection		threaded connection G 1/4 Internal thread	
Application			
System		gold-plated contacts	
Application		for industrial applications	
Media		liquids and gases	
Medium temperature	[°C]	-2580	
Min. bursting pressure	[kPa]	3000	
Pressure rating	[kPa]	1000	
Type of pressure		relative pressure	
Electrical data			
Operating voltage	[V]	1830 DC	
Current consumption	[mA]	< 50	
Min. insulation resistance	[MΩ]	100; (500 V DC)	
Protection class		III	
Reverse polarity protection		yes	
Power-on delay time	[s]	0.2	
Integrated watchdog		yes	

PZ9987

Pressure sensor with LED bar display

PZ-001KRBR14-HFPKG/US/...V



Inputs / outputs			
Number of inputs and outp	uts	Nun	nber of digital outputs: 1
Outputs			
Total number of outputs			1
Output signal			switching signal
Electrical design			PNP
Number of digital outputs			1
Output function		normally	open / closed; (configurable)
Max. voltage drop switching output DC	g [V]		2
Permanent current rating o switching output DC	of [mA]		250
Switching frequency DC	[Hz]		10
Short-circuit protection			yes
Type of short-circuit protection		yes (non-latching)	
Overload protection			yes
Measuring/setting range			
Measuring range	[kPa]		0100
Set point SP	[kPa]	5100	
Reset point rP	[kPa]		398
In steps of	[kPa]		1
Note on hysteresis			adjustable
Accuracy / deviations			
Switch point accuracy [% of the final value]		< ± 2,0	
Repeatability		$< \pm 0.25$; (with temperature fluctuations < 10 K)	
	nal valuel	$< \pm 0.25$; (with	n temperature fluctuations < 10 K)
[% of the fir		< ± 0,25; (with	, , , , , , , , , , , , , , , , , , ,
[% of the fir Temperature drift per 10 K		< ± 0,25; (with	temperature fluctuations < 10 K) < ± 0.3
[% of the fir Temperature drift per 10 K Software / programming			< ± 0.3
[% of the fir Temperature drift per 10 K			, , , , , , , , , , , , , , , , , , ,
[% of the fir Temperature drift per 10 K Software / programming Adjustment of the switch			< ± 0.3
[% of the fir Temperature drift per 10 K Software / programming Adjustment of the switch point			< ± 0.3
[% of the fir Temperature drift per 10 K Software / programming Adjustment of the switch point Operating conditions			< ± 0.3 Programming button
[% of the fir Temperature drift per 10 K Software / programming Adjustment of the switch point Operating conditions Ambient temperature	[°C]		< ± 0.3 Programming button -2580
[% of the fir Temperature drift per 10 K Software / programming Adjustment of the switch point Operating conditions Ambient temperature Storage temperature Protection	[°C]		< ± 0.3 Programming button -2580 -40100
[% of the fir Temperature drift per 10 K Software / programming Adjustment of the switch point Operating conditions Ambient temperature Storage temperature	[°C]		< ± 0.3 Programming button -2580 -40100
[% of the fir Temperature drift per 10 K Software / programming Adjustment of the switch point Operating conditions Ambient temperature Storage temperature Protection Tests / approvals	[°C]		< ± 0.3 Programming button -2580 -40100 IP 65
[% of the fir Temperature drift per 10 K Software / programming Adjustment of the switch point Operating conditions Ambient temperature Storage temperature Protection Tests / approvals	[°C]	EN 61000-4-2 ESD	< ± 0.3 Programming button -2580 -40100 IP 65 4 kV CD / 8 kV AD
[% of the fir Temperature drift per 10 K Software / programming Adjustment of the switch point Operating conditions Ambient temperature Storage temperature Protection Tests / approvals EMC	[°C]	EN 61000-4-2 ESD EN 61000-4-3 HF radiated EN 61000-4-4 Burst EN 61000-4-6 HF conducted	< ± 0.3 Programming button -2580 -40100 IP 65 4 kV CD / 8 kV AD 10 V/m 2 kV 10 V
[% of the fir Temperature drift per 10 K Software / programming Adjustment of the switch point Operating conditions Ambient temperature Storage temperature Protection Tests / approvals EMC Shock resistance	[°C]	EN 61000-4-2 ESD EN 61000-4-3 HF radiated EN 61000-4-4 Burst EN 61000-4-6 HF conducted DIN IEC 68-2-27	<pre>< ± 0.3 Programming button -2580 -40100 IP 65 4 kV CD / 8 kV AD 10 V/m 2 kV 10 V 50 g (11 ms)</pre>
[% of the fir Temperature drift per 10 K Software / programming Adjustment of the switch point Operating conditions Ambient temperature Storage temperature Protection Tests / approvals EMC Shock resistance Vibration resistance	[°C]	EN 61000-4-2 ESD EN 61000-4-3 HF radiated EN 61000-4-4 Burst EN 61000-4-6 HF conducted	< ± 0.3 Programming button -2580 -40100 IP 65 4 kV CD / 8 kV AD 10 V/m 2 kV 10 V
[% of the fir Temperature drift per 10 K Software / programming Adjustment of the switch point Operating conditions Ambient temperature Storage temperature Protection Tests / approvals EMC Shock resistance	[°C]	EN 61000-4-2 ESD EN 61000-4-3 HF radiated EN 61000-4-4 Burst EN 61000-4-6 HF conducted DIN IEC 68-2-27 DIN IEC 68-2-6	<pre>< ± 0.3 Programming button -2580 -40100 IP 65 4 kV CD / 8 kV AD 10 V/m 2 kV 10 V 50 g (11 ms)</pre>

PZ9987

Pressure sensor with LED bar display





Materials (wetted parts)	FKM; ceramics; stainless steel (1.4305 / 303)
Min. pressure cycles	100 million
Process connection	threaded connection G 1/4 Internal thread

Displays / operating elements		
Display	Switching status	LED, yellow
	Measured values	10 x LED, green Resolution 10 % of the final
		value

Remarks	
Pack quantity	1 pcs.

Electrical connection

Connector: 1 x M12; coding: A; Contacts: gold-plated





